Wilson Electronics Say Goodbye to Dropped Calls

800/1900 MHz

Sleek™ Cellular Signal Booster



SPECIFICATIONS

Part Number	815225
Frequency	824-894 MHz / 1850-1990 MHz
Gain	20 dB
Max Output Power	31.8 dBM
Noise Figure	3.0 dB nominal
Flatness	±4 dB
Isolation	> 40 dB
Power Requirements	5V
Connectors	SMA Female
Dimensions	$2.25 \times 4.25 \times 2.5$ (inch) $5 \times 9.5 \times 5.6$ (cm)
Weight	2.5 (oz) / 0.07 (kg)

FEATURES

- Portable can easily be moved between vehicles
- Reduces dropped calls, extends signal range, and increases data rates
- Amplifies signals to and from cell tower
- Up to 20 TIMES more output power to cell tower (when in a vehicle)
- Receives weak signals the phone alone may not
- Built-in battery charging port (adapters sold separately)
- Extends battery life Booster enables phone to work at reduced power
- Adjustable arms to fit any phone
- Simplifies hands free operation
- Installs in minutes no special tools required
- Package includes everything needed -- plug-and-play
- Attractive, compact design

KIT

Wilson Electronics new Sleek™ improves both voice and data performance indoors. With 20 times the power to the cell tower of a cell phone alone, it features a built-in antenna, battery charging port and works with Cellular (800 MHz) and PCS (1900 MHz) frequencies.

The Wilson Electronics' Sleek Signal Booster kit (815226) includes:*

- Sleek[™] all-in-one cradle and signal booster
- Outside vehicle mini magnet-mount antenna
- Power adapter**
- 30-day money-back guarantee
- One-year product warranty
- * In-Home accessory kit (859970) available
- ** Use only with Wilson power supply

